



Product Catalog

WPG Series
Potentiostat/Galvanostat



For
Corrosion
Material Testing
Sensor/Bioelectrochemistry
Battery/Fuel Cell
Supercapacitor/Solar Cell

Potentiostat/Galvanostat

- Economical price
- 16bit ADC, DAC
- For long term experiment
- Accurate control & measurement
- User friendly software
- Free software upgrade
- Local area network(LAN) for communication
- Current ranges: 8 ranges for WPG100ex, 6 ranges for WPG100S & WPG100H8, 4 ranges for WPG100H12, & 3 or 1 current ranges for WPG100HP Series
- Importing/exporting data file

The **WPG series** are well suited for general electrochemical experiments including battery testing, corrosion measurements and electrochemical research applications.

● For Stable and Accurate Target

- 4 Kelvin probe type true Potentiostat/Galvanostat circuit
- With 16bit ADC, DAC, this system provides 0.0015% f.s. high resolution in control and data acquisition.
- Multiple current ranges(auto/manual selection)
 - WPG100ex: 8 ranges
 - WPG100S, WPG100H8: 6 ranges
 - WPG100H12: 4 ranges
 - WPG100HP: 3 or 1 range depending on system
- User specification is available from low current to high current
- Temperature measurement input: (standard)
 - K-type thermocouple (option)
- Auxiliary voltage measurement(standard)-Aux V cable (option)
- Shield cell cable to protect EMI noise
- Automatic firmware upgrade
- LAN communication network
- This system can be used for battery cyclers.

● Safety Limit & Fail Check Functions

- To protect hardware, this system stops the experiment automatically when it meets or exceeds the hardware specification or user defined safety limit.
- User defined safety condition setting: User can input safety level depending on chemical properties of reactants in test cell.
- Unique "Fail check" function: To protect the system and cell itself, the experiment will be stopped automatically when the measured value is different from control value due to battery failure or wrong cell connection, etc.
 - e.g. Control value: 1Amp, Measured value: 500mA Then the potentiostat will stop automatically.
- Automatic cell connection check: Before experiment, if the cell voltage value is over the range of setting value, program gives the warning message for the operator to check the cell connection.
- If operator does press stop button by mistake, confirmation message box appears.
- If main program is down by unstable operating system, independent server program keeps the experiment (control & data acquisition) without dead time.
- Easy calibration with verification function

● Cell kits



Corrosion Cell Kit



Flat Cell Kit



Plate Test Cell



Plate Test Cell


- Pt Plate Counter Electrode
 - active area(Pt plate) : 1, 4, 5cm²



- Faraday Cage



- Universal Electrode Holder
 - electrode and glass vial are not included.



- Battery Jigs
 - Single universal jig
 - Single pouch cell jig



Single Universal Jig




Single Pouch Cell Jig

Software (Smart Interface)

- 32bit/64bit OS environment
- TCP/IP communication
- Max. 200 steps
- Max. 10 cutoff(vertex) condition
- Max. 300,000 data point memory on control board
- Virtual control panel
- Various real time plots & universal axis graphs
- Data backup function
- WYSIWYG graphics
- User friendly software


Virtual Control Panel



- BCO(button click operation): User can do any task just by clicking the button. No Menu Selection.
- Easy assignment of cycle test condition file
- It displays real time graphics(V vs. I, V & I vs. time, V vs. logI etc.) to fit its own techniques. This can be selected by graphic short cut icon.



- Status bar displays the potentiostat status.
- Various task functions: run, stop, suspend, moving step, etc. Spying the contents of test program which were assigned to potentiostat
- Experiment parameters can be saved or loaded on the virtual control panel.
- On experiment running, users can analysis data or other tasking simultaneously.
- Real time strip chart display




- User can nominate folder for saving data.
- Value of Interest(VOI) display function

Elapsed Time	Voltage(V)	Current(A)	Power(W)	Auxiliary(V)	Temperature(°C)
00:00:29	34.8m	33.2u	1.2u	180.1m	0.0

- Various safety function (Safety limit setting etc)

Schedule Editor



- One stop test condition creation/modification
- Parameter mixed input system
- Max. 200 of test steps
- Control parameters are
 - Constant voltage
 - Constant current
 - Constant power
 - Constant load
 - C-rate
 - Voltage scanning
 - Conditioning potential
 - Conditioning current
 - Rest
 - LastVscan
 - CstepV (Staircase Voltage Sweep)
 - CstepI (Staircase Current Sweep)
 - CC/CV
- Step flow are defined by next step, loop and cycle
- Cut-off conditions can be set by:
 - step time, voltage, current, dV/dt, dI/dt, cycle time, loop time, capacity, -dV, Whr, temperature, Aux voltage,, dT/dt,


No	Turn Step	Type	Cond.	Value	dt	And	Typ
1	Next Step	Step Time	≥	30.00			

Step No	Step Name	Type	Value (Scan Rate)	Range / Loop	T

- Data sampling condition by each step:
 - time, dV/dt, dI/dt, dT/dt, dV2/dt
- And/Or logic for cut-off condition setting

Pre-defined Techniques

- This system provides pre-defined technique menu and universal test procedure menu for user to make their own experiment procedure with cycle, loop and/or logic.
- Predefined technique menu



Electroanalytical Techniques

- Cyclic voltammetry
- Linear sweep voltammetry
- Chrono-amperometry
- Chrono-coulometry
- Chrono-potentiometry

Corrosion Measurement

- Tafel plot
- Potentiodynamic
- Potentiostatic
- Galvanostatic
- Cyclic polarization
- Ecorr vs. time
- Linear polarization resistance

Potentiostat/Galvanostat WPG Series

Energy Test

- CC/CV (Lithium battery) test menu
- CC/CC (NiCd(NiMH) battery) test menu
- Steady state CV
- Pstat IV curve
- Gstat IV curve
- EVS (Electrochemical voltage spectroscopy) test
- GITT (Galvanostatic intermittent titration technique) test
- PITT (Potentiostatic intermittent titration technique) test


Real Time Data Monitor

ITEM	VALUE
Flow Status	Running
CC Status	CC-ON
Schedule File	WPG1
Technique Name	Test
Elapsed Time	000014
Loop No.	1
Loop Time	000014
Cycle No.	1
Cycle Time	000014
Step No.	2
Step Time	000014
Control Type	VSCAN
I Range	1mA
OCV Value	1.52486V
Data File	20141009175036_003.wrd
Data Point	65
Current File Size	73 kb/45


- Displayed test data: status, running time, step number, cycle number, step time, current range, current, voltage, capacity, power, energy, Aux V, Calc V, temp, cycle file name, data file name, and file size.

Graphics

- Multiple plot format
 - General graph
 - Cycle graph




General graph format





Cycle graph format

General Function of Graph



- Multi-parameters
- Plot overlay: max. 20 plot
- Universal graphics: any combination of X,Y1,Y2,Y3,Y4 axis parameters
- Automatic updating plot with reloading button for running experiment data
- Automatic/Manual scale and polarity selection for each axis




- Cross-hair pointer by mouse click/arrow key displays coordinate values on graph
- Mouse zooming
- Density, specific value display



- Copy to clipboard function to use in other application software
- Grid on/off and dot/line selection
- ASCII file conversion or Excel file conversion of graph data only




- Parameter change without reloading the data file
- Data set On/Off: Data can be visible or invisible by selecting/deselecting the data set.
- Rest step data hidden function
- Advanced graph setting



Voltage vs. |charging-discharging capacity| graph


Tools

- Data Editor
 - General data report
 - Cycle data report




- * Data editing
- * Data filtering


- Data Conversion
 - Multiple data conversion(ASCII, Excel)



- Data file splitter by cycle number



- Calibration
 - User can calibrate the potentiostat.
- Data backup



- Split data file

Independent Data Analysis Software



The WPG data format can be used for independent data analysis software IVMAN™ at free of charge.


IVMAN™ software package consists of

- IVMAN software
- IVMAN differential analysis software
- IVMAN photo voltaic cell analysis.
- IVMAN Tafel analysis
- IVMAN extractor
- IVMAN peak find module




IVMAN DA™ Battery Test Data Analysis Software

- Battery test data analysis
- Electrochemical voltage spectroscopy (dQ/dV vs. V)
- Voltage vs. Capacity analysis (V vs. Q)
- Cycle graph (Q vs. cycle)
- Differential voltage graph(dV/dQ vs. Q)



Measured data

V vs. Q




Cycle graph

dQ/dV vs. V



IVMAN™ Photovoltaic Cell Analysis




- Automatic analysis of parameters
- open circuit voltage, open circuit current, max. power, efficiency
- photo induced current, diode quality factor, series resistance, etc.




IVMAN™ Tafel Analysis

- Simple Tafel calculation




IVMAN™ Main Software

- Electrochemical analysis software
- Ideal for DC corrosion data analysis and electro-analytical data analysis
- Initial guessing function on Tafel analysis
- Automatic Tafel fitting
- Polarization resistance fitting
- 3D graph
- Find peak function
- Interpolation, differentiation, integration, etc.
- Reporting function




Tafel initial fitting

Tafel analysis result




Polarization resistance fitting

Polarization analysis result



Time graph

Find peak menu




CV graph

3D graph


Extractor

- Extracting data by cycle number or step
- Exporting ASCII file



Peak Find Module

- Independent peak finding software



WPG100ex Standard Type



Application

- Corrosion test
- Sensor application
- General electrochemistry
- Battery/Super capacitor/Fuel cell test
- Material test

The **WPG100ex** is an economical research grade potentiostat system which is designed for general electrochemistry, corrosion, battery, etc. It has a power of $\pm 1A$ and low current ranges, down to 100nA full scale as standard. And customized specification is available upon request. The **WPG100ex** is designed with a local area network(LAN) for communication with a computer. Temperature input and auxiliary voltage input are included.

Specifications

Control voltage range	$\pm 10V$ (standard)
Compliance voltage	$\pm 12V$ (standard)
Control current range	1A, 8 ranges (standard)
LED	Run: 1ea, Mode: 2ea, I range: 8ea
Input impedance	10^{12} Ohm
Cell connection	6 probe type, alligator clip cables
Voltage accuracy	$\pm 0.02\%$ f.s.
Current accuracy	$\pm 0.02\%$ at 10uA to 1A range $\pm 0.1\%$ at 1uA, 100nA range

Voltage Control/Measurement

Full scale ranges (within 40 Watt)	$\pm 10V$ (standard) $\pm 20V$ or $\pm 40V$ (optional)
Resolution (16 Bits)	0.3mV(standard)

Current Control/Measurement

Full scale ranges	$\pm 10V@1A$ (standard) $\pm 20V@1A$, $\pm 40V@500mA$ (optional)
Resolution	16 bit(0.0015% f.s)
Power	40Watt
Sampling time	1msec
Communication	TCP/IP
Size	300x300x80mm (WxDxH)

All specifications are subject to change without notice.

WPG100S Potentiostat/Galvanostat



Application

- General electrochemical application
- Corrosion/electroplating
- Electrosynthesis/Electrolysis
- Battery test/Supercapacitor test
- Fuel cell test
- Solar cell test

The system hardware is based on WPG series potentiostat/galvanostat and designed for general electrochemical application such as corrosion, battery test, photoelectrochemistry, and fuel cell, electroplating etc with 6 current ranges. Temperature input and auxiliary voltage input are included.

Maximum power is 400Watt and the customize specification is available within this power. The **WPG100S** is designed with a local area network(LAN) for communication with a computer. Bipolar model's max voltage is $\pm 40V$ Volts.

Specifications


Control current range	6 ranges
LED	Run: 1ea, Mode: 2ea, I range: 6ea
Input impedance	10^{12} Ohm
Cell connection	4 probe type, alligator clip cables
Voltage accuracy	$\pm 0.05\%$ f.s. ($<10V$)
Current accuracy	$\pm 0.05\%$ f.s.

Voltage Control/Measurement

Full scale ranges	Refer to power configuration map
Resolution (16 bits)	0.0015% f.s

Current Control/Measurement

Full scale ranges



Max. f.s under 400Watt

Bipolar voltage range

- 1) Max 26A @ $\pm 5V$ (C5V*)
- 2) Max 5A @ $\pm 5V$ (C10V*)
- 3) Max 5A @ $\pm 10V$ (C12V*)
- 4) Max 16A @ $\pm 10V$ (C10V*)
- 5) Max 13A @ $\pm 10V$ (C15V*)
- 6) Max 8A @ $\pm 20V$ (C21V*)
- 7) Max 5A @ $\pm 30V$ (C31V*)
- 8) Max 1A @ $\pm 40V$ (C43V*)
- 9) Max 4A @ $\pm 40V$ (C43V*)

* Compliance voltage

Unipolar voltage range

- 1) Max 37A @ -1V to 5V
- 2) Max 26A @ -1V to 10V
- 3) Max 14A @ -1V to 21V
- 4) Max 10A @ -1V to 31V
- 5) Max 7A @ -1V to 43V

Resolution	16 bit (0.0015% f.s)
Communication	TCP/IP
Sampling time	1msec
Size	447x188x491.2mm (WxDxH)

All specifications are subject to change without notice.

WPG100H8/H12 Power Potentiostat/Galvanostat



Application

- High power application / Electrosynthesis/Electrolysis
- Battery test/Supercapacitor test / Fuel cell test
- Solar cell test / Pilot line application

The system hardware is based on WPG series potentiostat/galvanostat and designed for high power application with 6 or 4 current ranges. Maximum power is 800Watt(WPG100H8) or 1200Watt(WPG100H12). The customize specification is available within this power. Temperature input and auxiliary voltage input are included

Specifications

Control current range	WPG100H8: 6 ranges WPG100H12: 4 ranges
LED	Run: 1ea, Mode: 2ea Irange: 3ea
Input impedance	10^{12} Ohm
Cell connection	4 probe type, alligator clip cables
Voltage accuracy	$\pm 0.05\%$ f.s. (<10V)
Current accuracy	$\pm 0.1\%$ f.s.


Voltage/Current Control/M Measurement

Refer to Power configuration Map

Resolution (16 bits)	0.0015% f.s
----------------------	-------------

Power Configuration

Full scale ranges



Max. fs under 800Watt (H8)

Bipolar voltage range


- 1) Max 52A @ $\pm 5V$ (C5V*)
- 2) Max 32A @ $\pm 10V$ (C10V*)
- 3) Max 25A @ $\pm 10V$ (C10V*)
- 4) Max 16A @ $\pm 20V$ (C21V*)
- 5) Max 8A @ $\pm 40V$ (C43V*)

* Compliance Voltage

Unipolar voltage range

- 1) Max 60A @ -1V to 5V
- 2) Max 50A @ -1V to 10V
- 3) Max 29A @ -1V to 21V
- 4) Max 26A @ -1V to 24V
- 5) Max 20A @ -1V to 31V
- 6) Max 15A @ -1V to 43V

Full scale ranges



Max. fs under 1200Watt (H12)

Bipolar voltage range

- 1) Max 61A @ $\pm 5V$ (C5V*)
- 2) Max 50A @ $\pm 10V$ (C10V*)
- 3) Max 40A @ $\pm 10V$ (C10V*)
- 4) Max 25A @ $\pm 20V$ (C21V*)
- 5) Max 12A @ $\pm 40V$ (C43V*)

* Compliance voltage

Unipolar voltage range

- 1) Max 78A @ -1V to 10V
- 2) Max 43A @ -1V to 21V
- 3) Max 39A @ -1V to 24V
- 4) Max 30A @ -1V to 31V
- 5) Max 23A @ -1V to 43V

Communication	TCP/IP
Sampling time	1msec
Emergency switch	Located on the front panel
Size	H8: 447.1x241x505.2mm (WxDxH) H12: 464.1x285.4x626mm (WxDxH)

All specifications are subject to change without notice.

WPG100HP High Power Potentiostat/Galvanostat



Application

- High power application
- Electrosynthesis/Electrolysis
- Battery test/Supercapacitor test
- Fuel cell test
- Solar cell test
- Pilot line application

The system hardware is based on WPG series potentiostat/galvanostat and designed for high power application such as battery pack, solar module, and fuel cell stack, electroplating etc with 1 or 3 current ranges depending on system. Maximum power is 4kWatt and the customize specification is available within this power. The WPG100HP is designed with a local area network(LAN) for communication with a computer. Bipolar model's max voltage is $\pm 45V$ Volts. Temperature input and auxiliary voltage input are included.

U model (WPG100HPU) is unipolar model (positive voltage only) for Energy research. Max voltage is 0 to 90V available.

Specifications


Control current range	1 or 3 ranges depending on power
LED	Run: 1ea, Mode: 2ea
Input impedance	10^{12} Ohm
Cell connection	4 probe type, alligator clip cables
Voltage accuracy	$\pm 0.1\%$ f.s.
Current accuracy	$\pm 0.1\%$ f.s.

Voltage Control/M Measurement

Full scale ranges	Refer to power configuration map
Resolution (16 bits)	0.0015% f.s

Current Control/M Measurement

Full scale ranges



Maximum current depending on voltage range

1. voltage bipolar

- 1) Max 200A @ $\pm 5V$ (C7V*)
- 2) Max 150A @ $\pm 10V$ (C10V*)
- 3) Max 76A @ $\pm 10V$ (C10V*)
- 4) Max 76A @ $\pm 20V$ (C21V*)
- 5) Max 72A @ $\pm 24V$ (C24V*)
- 6) Max 46A @ $\pm 30V$ (C31V*)
- 7) Max 38A @ $\pm 40V$ (C43V*)

* Compliance voltage

2. voltage unipolar

- 1) Max 180A @ -2V~+10V
- 2) Max 140A @ -2V~+21V
- 3) Max 95A @ -2V~+31V
- 4) Max 76A @ -1V~+43V
- 5) Max 42A @ -1V~+50V
- 6) Max 46A @ -1V~+68V
- 7) Max 46A @ -1V~+77V


Resolution	16 bit (0.0015% f.s)
Communication	TCP/IP
Sampling time	1msec
Emergency switch	Located on the front panel

All specifications are subject to change without notice.



WonATech Co., Ltd.
7, Neunganmal 1-gil, Seocho-gu,
Seoul, 06801, Korea
Phone: +82-2-578-6516
Fax: +82-576-2635
e-mail: sales@wonatech.com
website: www.wonatech.com

Local Distributor



ISO 9000 & ISO 14000 Qualified